



MOD008 Update Procedure – Reverse Power Option

Note: In order to upgrade your SR750 or SR760 Feeder Management Relay to include MOD 008 (Reverse Power), you will require a 16-digit passcode that can be purchased from our Sales Department. The relay's firmware revision also needs to be at 5.00 or greater. The latest firmware can be downloaded from our Internet site at www.GEIndustrial.com/Multilin. Should you require assistance at any time during this procedure, please contact our Technical Support Department (numbers listed at the end of this procedure).

MOD008 ENABLE PROCEDURE:

Step 1: Press **S1** to display:

SETPOINTS
S1 RELAY SETUP

Step 2: Keep pressing **MESSAGE DOWN** until this message appears:

MOD 008 UPGRADE
[ENTER] for more

Step 3: Press **ENTER** then this message will appear:

ENABLE MOD 008?
Disabled

Step 4: Press **VALUE DOWN** once then this message will appear:

ENABLE MOD 008?
Enabled

Step 5: Press **ENTER**, then this message will appear temporarily:

NEW SETPOINT STORED

Step 6: Press **MESSAGE DOWN** once then this message will appear:

ENTER PASSCODE:
0000000000000000



- Step 7: Press **ENTER** and a cursor will appear
- Step 8: Press the **VALUE UP** key to change the number to match the 16 digit code number then Press **ENTER** to move to the next number. Continue this process until all numbers are entered. After entering the last number the cursor should move to the first digit of the code
- Step 9: Press **MESSAGE DOWN** and this message will appear:
- UPGRADE OPTIONS?
NO
- Step 10: Press **VALUE DOWN** once, the message will change to:
- UPGRADE OPTIONS?
YES
- Step 11: Press **ENTER** then this message will temporarily appear:
- NEW SETPOINT STORED
- Step 12: Wait 30 seconds and then turn the power to the relay off and back on.
- Step 13: After the relay powers up this message will now be displayed:
- GE Power Management
760 REV 5.00 MOD 008
- Step 14: MOD 008 is now enabled.

Should you require assistance at any time during this procedure, please contact us at one of the numbers below:

Technical Support Lines:

Within US/Canada: **1-800-547-8629**
Outside US/Canada: **+1(905) 294-6222**
Fax: **+1(905) 201-2098**

Email:

gmultilin@indsys.ge.com